


# Contatore elettronico di energia elettrica monofase digitale

Digital electronic single phase energy meter



50-60 Hz - 230 Vac  
 Corrente di base Ib 5 A  
 Corrente massima 45 A  
 Risoluzione di lettura 0,1 kWh  
 Precisione classe 1  
 Numeratore 6 digit + 1 decimale  
 Autoconsumo < 0,4 W  
 Corrente di avviamento 20 mA  
 Inserzione diretta  
 Sezione cavi da 1,5 ... 6 mmq  
 Display retroilluminato  
 Misure visualizzabili:  
 Energia attiva kWh totale (non azzerabile)  
 Energia attiva kWh parziale (azzerabile)  
 Potenza attiva istantanea rilevata  
 Tensione  
 Corrente  
 Fattore di potenza  
 Frequenza

50-60 Hz - 230 Vac  
 Base current Ib 5 A  
 Max current 45 A  
 Reading resolution 0,1 kWh  
 Precision class 1  
 Numbering 6 digital + 1 decimal  
 Power consumption < 0,4 W  
 Start current 20 mA  
 Direct connection  
 Wires section from 1,5 ... 6 mmq  
 Backlighted display  
 Measures displayed:  
 Total active energy kWh (not resettable)  
 Partial active energy kWh (resettable)  
 Instantaneous active power detected  
 Voltage  
 Current  
 Power factor  
 Frequency



CODICE	CORRENTE MASSIMA (I max)	MODULO	PESO
CODE	MAX CURRENT (I max)	MODULE	WEIGHT
	A	DIN	gr
<b>CE201DI</b>	45	1	90