

Sensore infrarossi di prossimità a sfioramento ON/OFF

ON/OFF infrared proximity sensor



230 Vac - 50-60 Hz
Carico max incandescenza 500 W
Carico max LED 230/fluorescenza 200W
Corrente nominale 5A
Distanza di rilevamento 5-6 cm
Grado di protezione IP20
Lunghezza cavo sensore 1,5m

230 Vac - 50-60 Hz
Max load incandescent 500W
Max load LED 230/fluorescent 200W
Rated current 5A
Detection distance 5-6 cm
IP rating IP20
Sensor cable lenght 1,5m



Adatto per sotto pensili. Il suo stato è controllato dal movimento della mani. Quando si avvicina la mano al sensore IR, questo rileva il movimento e accende il carico che rimarrà acceso fino a quando il sensore IR rileverà un altro movimento della mano, spegnendolo.

Suitable for under-cabinet installation. Its state is controlled by hand movements. When a hand approaches the IR sensor, it detects the motion and turns on the load, which remains on untile the IR sensor detects another hand movement, turning it off.

CODICE	FUNZIONAMENTO	COLORE	POTENZA MAX INCANDESCENZA	POTENZA MAX FLUORESCENZA	POTENZA MAX LED 230V	DISTANZA DI RILEVAZIONE	PESO
CODE	OPERATION	COLOUR	MAX INCANDESCENT POWER	MAX FLUORESCENT POWER	MAX POWER LED 230V	DETECTION DISTANCE	WEIGHT
			W	W	W	cm	gr
SE008BI	ON / OFF	Bianco / White	500	200	200	5-6	100